

Athens, Ohio Area Packet Radio Temporary, Experimental Network Interconnect Diagram (As of December 29, 2023 - Subject to Change)

HEBRON, OHIO (30 mi E of Columbus)

HEBSW1:K8QIK-11} Ports:

Port Freq: Links to:

```

-----
1 144.390 MHz (APRS Receive only)
2 145.050 MHz -> Local user port
3 223.660 MHz -> Link port
4 441.500 MHz -> to KB8UVN-7 Switch -----+
5 446.975 MHz
6 AX/IP/UDP
7 AXUDP Hub

```

^

|

|

|

|

145.05 mHz

^

|

ATHENS:W8KVK-7}

Available commands: Bye Connect CQ

Heard Info Nodes Routes Users

|

Athens Users Start Here on 145.05 mHz

Command: "C ATHENS"

Then "C K8QIK-11" for Hebron Node

From K8QIK-11, you ***must*** specify a port#.

eg: "C 4 KB8UVN-7" Append 'S' to this

command if you want to S(tay) on the

Hebron Node after disconnecting from

any KB8UVN-7 port. eg: C 4 KB8UVN-7 S

For Ohio County-by-County node lists

visit <https://ohiopacket.org>

JOHNSTOWN, OHIO

JTSW1:KB8UVN-7) Ports

Port Freq: Note:

```

-----
1 28.120 MHz LSB 1200 Baud
2 50.640 MHz 1200 Baud
3 144.390 MHz 1200 Baud
4 145.010 MHz 1200 Baud
5 145.730 MHz 1200 Baud
6 223.660 MHz 1200 Baud
7 434.975 MHz 9600 Baud
8 438.050 MHz 2400 Baud
9 440.150 MHz 1200 Baud
+->10 441.500 MHz 1200 Baud
11 445.925 MHz 1200 Baud
12 446.975 MHz 1200 Baud
13 3.5890 MHz 300 Baud
14 7.1040 MHz 300 Baud
15 10.1510 MHz 300 Baud
16 14.1050 MHz 300 Baud
17 3.5860 MHz USB ARDOP
18 7.1010 MHz USB ARDOP
19 14.1020 MHz USB ARDOP
20 3.5860 MHz VARA
21 7.1010 MHz VARA
22 14.1020 MHz VARA
23 10.1474 MHz Robust Packet
24 145.730 MHz VARA FM
25 AX/IP/UDP
26 AXUDP Hub
27 Telnet Server
28 10.1476 MHz VARA KISS

```

BBS: KB8UVN-1 / Node: KB8UVN-7

RMS (Winlink) Gateway: KB8UVN-10 /

NET105: 14.105 MHz / NET40: 7.104 MHz

Available commands: BBS RMS QSO CONNECT

BYE INFO NODES PORTS ROUTES USERS MHEARD

Questions always welcome;

73 de Ted@W8KVK.com